

NetGear R7000p Setup Guide




Contents

1	Reset router	1
2	Setup router	1
	Ethernet cable connection	1
	WiFi connection.....	2
3	Login WIFI configuration page	2
4	Optional: Change your WiFi name and password/PIN.....	5


1 Reset router

- 1.1 Connect the router to power supply.
- 1.2 Press and hold this button for more than 10 seconds to reset the router to its factory default settings.



2 Setup router

- 2.1 Using an Ethernet cable to connect the WAN port.



- 2.2 There are two methods to connect with your router:

Ethernet cable connection


- 2.3 Turn off the WiFi on your laptop/PC and connect laptop/PC with any of LAN ports (1 –4 of router) via Ethernet cable.



WiFi connection

You can use your laptop, tablet or phone to connect with router for setting through WiFi.

2.4 You can find the WiFi name and password/PIN at this label of router.




2.5 Click the network icon of your computer or go to Wi-Fi Settings of your smart device, and then select the SSID to join the network.

***Careful:** Once your device connect with haven't configured router, your device will temporarily out of Internet. So please do not use the device which is currently using Internet.

3 Login WIFI configuration page

3.1 Open Internet browser (e.g. Google Chrome, Safari, etc.) and input <http://192.168.1.1/> or <http://192.168.0.1/> in the address bar to visit router's


configuration page. The user name is **admin**. The default password is **password**. (all Lowercase)




3.2 Once you login, on the side bar, click Advanced



3.3 Then choose Internet Setup.



3.4 Choose Yes in Does Your Internet Connection Require A Login?



BASIC **ADVANCED** English

Basic Settings Test Cancel Apply

Does your Internet connection require a login?

☒ Yes
☐ No

Account Name (If Required) JNR1010

Domain Name (If Required)

Internet IP Address


☒ Get Dynamically From ISP
☐ Use Static IP Address

IP Address 0 0 0 0

IP Subnet Mask 0 0 0 0

Gateway IP Address 0 0 0 0

3.5 Change Internet Service Provider to PPPoE



BASIC **ADVANCED** English

Basic Settings Test Cancel Apply

Does your Internet connection require a login?

☒ Yes
☐ No

Internet Service Provider PPPoE

Login


Password

Service Name (If Required)

Connection Mode Always On

Idle Timeout (In minutes) 5

3.6 Input the PPPoE username and password provided by us, then click “Save”. You can find these username and password in the Service Activation Notice Email. (Ensure the Connection Mode is Always on and please save other as default.)



BASIC **ADVANCED** English

Basic Settings Test Cancel Apply

Does your Internet connection require a login?

☒ Yes
☐ No

Internet Service Provider PPPoE

Login

Password

Service Name (If Required)

Connection Mode Always On

Idle Timeout (In minutes) 5

Username and Password

Always on

3.7 After a while, the second on the left light of your router is solid green which means you can access the Internet now.




4 Optional: Change your WiFi name and password/PIN

4.1 Change WiFi name & Password:

In Basic Page, Click Wireless



You can enter your WiFi name in Wireless Name and Password in this page. Click "Apply" bottom after changing.



The image shows a 'Wireless Settings' configuration page. On the left is a sidebar with tabs: Home, Internet, Wireless (selected), Attached Devices, Parental Controls, and Guest Network. The main area has two sections: 'Wireless Network' and 'Security Options'. In the 'Wireless Network' section, the 'Name (SSID)' field contains 'JohnWIF' and is highlighted with a blue box and an orange arrow pointing to it with the text 'Change your WiFi name in here'. Below this, the 'Security Options' section has four radio buttons: 'None', 'WPA2-PSK [AES]', 'WPA-PSK [TKIP] + WPA2-PSK [AES]', and 'WPA/WPA2 Enterprise'. The 'WPA2-PSK [AES]' option is selected and highlighted with a blue box and an orange arrow pointing to it with the text 'Always this one'. Below the 'Security Options' section, the 'Password (Network Key)' field contains 'kindapple518' and is highlighted with a blue box and an orange arrow pointing to it with the text 'Change your WiFi password in here'. At the top right of the main area are 'Cancel' and 'Apply' buttons.

WIRELESS SETTINGS

Wireless Network

☒ Enable SSID Broadcast

Name (SSID): JohnWIF

Region: North America

Channel: Auto

Mode: Up to 150 Mbps

Security Options

☐ None

☒ WPA2-PSK [AES]

☐ WPA-PSK [TKIP] + WPA2-PSK [AES]

☐ WPA/WPA2 Enterprise

Security Options (WPA2-PSK)

Password (Network Key): kindapple518 (0-63 characters or 64 hex digits)

***Careful:** Once you change your WiFi name or password, your device needs to reconnect with WiFi.